

# Product datasheet

Specifications



## Lisse - Plate switch - without instructions - 3 gangs 2 way- 10AX White

GGBL1032NIS

### Main

Range	Lisse
Aesthetic name	White moulded
Product or component type	Plate switch
Device presentation	Complete product
Colour tint	White
Quantity per set	Set of 1

### Complementary

Switch function	2-way
Control type	Rocker
Number of gangs	3 gangs
Device mounting	Wall mounted
Rated current	10 AX at 230 V AC
Connections - terminals	Screw terminals
Material	Urea (carbamide)
Surface finish	Matt
Type of packing	Bag
Height	87 mm
Width	87 mm
Depth	25 mm
Product weight	0.096 kg

### Environment

Standards	BS EN 60669-1
IP degree of protection	IP20

### Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	2.500 cm
Package 1 Width	8.700 cm
Package 1 Length	8.700 cm

Excluding VAT, FCA Jabal Ali & are subject to change – check with your local distributor.

<b>Package 1 Weight</b>	97.700 g
<b>Unit Type of Package 2</b>	BB1
<b>Number of Units in Package 2</b>	10
<b>Package 2 Height</b>	9.500 cm
<b>Package 2 Width</b>	13.000 cm
<b>Package 2 Length</b>	18.500 cm
<b>Package 2 Weight</b>	1.054 kg
<b>Unit Type of Package 3</b>	CAR
<b>Number of Units in Package 3</b>	200
<b>Package 3 Height</b>	28.000 cm
<b>Package 3 Width</b>	38.500 cm
<b>Package 3 Length</b>	49.500 cm
<b>Package 3 Weight</b>	21.660 kg


## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.


[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better

 <b>Materials and Substances</b>	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant with Exemptions
REACH Regulation	<a href="#">REACH Declaration</a>
China RoHS Regulation	<a href="#">China RoHS declaration</a>

### Use Again

 <b>Repack and remanufacture</b>	
Take-back	No