

Product datasheet

Specifications



"Lisse - 2-way wide rocker switch - 1 gang - 10AX - white(Subject to availability)"

Local distributor code:

400142089

GGBL1012WS

⚠ To be discontinued on: 30 May 2025

⚠ To be discontinued

EAN Code: 3606480640766

Main

Range	Lisse
Aesthetic name	White moulded
Product or component type	Switch
Device presentation	Complete product
Colour tint	White
Quantity per set	Set of 1

Complementary

Switch function	2-way
Control type	Rocker
Number of gangs	1 gang
Device mounting	Wall mounted
Rated current	10 AX at 230 V AC
Connections - terminals	Screw terminals
Material	Urea (carbamide)
Surface finish	Matt
Type of packing	Bag
Height	87 mm
Width	87 mm
Depth	24 mm
Product weight	0.082 kg

Environment

Standards	BS EN 60669-1
IP degree of protection	IP20

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	2.800 cm
Package 1 Width	8.700 cm

Package 1 Length	8.700 cm
Package 1 Weight	89.900 g
Unit Type of Package 2	BB1
Number of Units in Package 2	10
Package 2 Height	9.500 cm
Package 2 Width	15.500 cm
Package 2 Length	18.500 cm
Package 2 Weight	978.400 g
Unit Type of Package 3	CAR
Number of Units in Package 3	200
Package 3 Height	33.000 cm
Package 3 Width	39.000 cm
Package 3 Length	50.000 cm
Package 3 Weight	20.195 kg

Logistical informations

Country of origin	CN
-------------------	----

Contractual warranty

Warranty	18 months
----------	-----------


Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant with Exemptions
REACH Regulation	REACH Declaration
China RoHS Regulation	China RoHS declaration

Use Again

 Repack and remanufacture	
Take-back	No